Auckland: (09) 2717 234
Christchurch: (03) 741 6241

sales@machineryhouse.co.nz
www.machineryhouse.co.nz

Product Brochure For G103

Electric Start Inverter Generator - GT2100ESi GT Power

2000W

Push Button Electric Start + Backup Recoil Start



ORDER CODE:	G103
MODEL:	GT2100ESi
Power Rating (Watts):	2000
Continuous Output (Watts):	1700
Phase (Type):	1
Engine Model (No.):	GT Power
Engine (Type):	4 stroke OHV
Noise Level @ 7 Metres (dB):	51
Start Method (Type):	Electric & Recoil
230V Power Socket (Qty):	1
230V Power Socket - Voltage & Plug Amps (V / Amp):	230 / 15
400V Power Socket (Qty):	~
400V Power Socket - Voltage & Plug Amps (V / Amp):	~
DC Power Outlet (Qty):	1
DC Power Socket - Voltage & Amps (V / Amp):	12 / 8.3
Fuel Tank Capacity (Litre):	4
Fuel (Type):	Unleaded
Operation Time @ 80% lOAD (hrs):	7
Dimensions (L x W x H) (mm):	500 x 280 x 450
Nett Weight (kg):	20

GT POWER

2 YEAR WARRANTY

Features

- 2000W (max) 1700W (rated).
- Push button electric start with EZ recoil backup makes starting effortless.
- 4-stroke powerdyne, air cooled, OHV industrial engine.
- 1 x 230V, 15amp power outlet & 1 x 12V DC, 8.3amp power outlet with bonus USB adapter.
- Optional parallel function increases power while maintaining the flexibility and convenience of compact design.
- 4L tank for up to 7 hours run-time (load dependent).
- Whisper quiet - only 51dB
- Highly portable and compact - under 20kg
- Featuring Eco mode button for efficient running.
- Wireless remote starting.
- Ideal for safe powering of sensitive electronics.