

Product Brochure For G109

Recoil Start Generator - Digital Inverter - GT3800Ei GT Power

3800W

Push Button Electric Start + Backup Recoil Start



ORDER CODE:	G109
MODEL:	GT3800Ei
Power Rating (Watts):	3800
Continuous Output (Watts):	3500
Phase (Type):	1
Engine Model (No.):	GT Power
Engine (Type):	4 stroke OHV
Noise Level @ 7 Metres (dB):	68
Start Method (Type):	Electric / Recoil
230V Power Socket (Qty):	2
230V Power Socket - Voltage & Plug Amps (V / Amp):	230 / 10
400V Power Socket (Qty):	~
400V Power Socket - Voltage & Plug Amps (V / Amp):	~
DC Power Outlet (Qty):	1
DC Power Socket - Voltage & Amps (V / Amp):	12 / 16.5
Fuel Tank Capacity (Litre):	10
Fuel (Type):	Unleaded
Operation Time @ 80% ILOAD (hrs):	11
Dimensions (L x W x H) (mm):	530 x 350 x 490
Nett Weight (kg):	34



Description

This revolutionary, super compact and powerful electric start inverter machines are designed and configured especially for NZ requirements in the construction and engineering markets.

The requirements for perfect sine wave inverter power is increasing year on year, and these new machines allow you to lead the market both in value and performance.

Features

- 3800W (max.) 3500W (cont.)
- Push button electric start with EZ recoil backup for easy starting
- Useful for battery chargers, drills, grinders, saws and lighting
- Robust and portable, weighing in at 34kg
- Powerdyne 4-Stroke OHV engine for ultimate durability.
- Smart throttle for quiet operation and fuel savings
- Twin 230V outlet + 2x USB outlets
- Fuel saving smart throttle feature
- Digital control panel for simplified engine management and parameters monitoring