

## Product Brochure For Z00890E

### Recoil Start Silenced Inverter Generator - PT2200i Powertec

2000W



|                                                       |                 |
|-------------------------------------------------------|-----------------|
| ORDER CODE:                                           | Z00890E         |
| MODEL:                                                | PT2200i         |
| Power Rating (Watts):                                 | 2000            |
| Continuous Output (Watts):                            | 1800            |
| Phase (Type):                                         | 1               |
| Engine Model (No.):                                   | Powertec        |
| Engine (Type):                                        | 4 stroke        |
| Noise Level @ 7 Metres (dB):                          | -               |
| Start Method (Type):                                  | Recoil          |
| 230V Power Socket (Qty):                              | 1               |
| 230V Power Socket - Voltage & Plug<br>Amps (V / Amp): | 230 / 15        |
| 400V Power Socket (Qty):                              | -               |
| 400V Power Socket - Voltage & Plug<br>Amps (V / Amp): | -               |
| DC Power Outlet (Qty):                                | -               |
| DC Power Socket - Voltage & Amps (V<br>/ Amp):        | -               |
| Fuel Tank Capacity (Litre):                           | 5               |
| Fuel (Type):                                          | Unleaded        |
| Operation Time @ 80% ILOAD (hrs):                     | 6               |
| Dimensions (L x W x H) (mm):                          | 498 x 298 x 459 |
| Nett Weight (kg):                                     | 22              |

POWERTEC



#### Description

The PT2200i is a compact lightweight machine capable of powering small, and sensitive, electrical appliances making it ideal for camping and home use applications.

1 x 15A 230V AC outlet ideal for operating lighting, small fridge/freezers, fans and much more.

#### Features

- 2000W (max.), 1800W (rated)
- 1x 15A, 230V outlet & twin USB outlets
- Reliable pure sine wave output performance
- Silenced casing & large capacity muffler for quiet operation
- Simple and reliable electronic ignition system
- Thermal overload circuit breakers for peace of mind
- High performance air cleaner system - greatly reduces engine wear and improves performance
- Large capacity muffler to minimise engine noise
- Optional parallel linking capability for increased power requirements & flexibility