

Product Brochure For Z00890J

Recoil Start Inverter Generator - GT3500SE

3300W



ORDER CODE:	Z00890J
MODEL:	GT3500SE
Power Rating (Watts):	3300
Continuous Output (Watts):	3000
Phase (Type):	1
Engine Model (No.):	GT Power
Engine (Type):	4 stroke OHV
Noise Level @ 7 Metres (dB):	65
Start Method (Type):	Recoil
230V Power Socket (Qty):	2
230V Power Socket - Voltage & Plug Amps (V / Amp):	230 / 10
400V Power Socket (Qty):	~
400V Power Socket - Voltage & Plug Amps (V / Amp):	~
DC Power Outlet (Qty):	~
DC Power Socket - Voltage & Amps (V / Amp):	~
Fuel Tank Capacity (Litre):	10
Fuel (Type):	Unleaded
Operation Time @ 80% ILOAD (hrs):	10
Dimensions (L x W x H) (mm):	578 x 440 x 510
Nett Weight (kg):	45



Description

Presenting GT Power's brand new GT3500SE inverter generator, This generator is powered by FM-SPWM ? frequency converter with its latest frequency conversion technology. It has a full power of 3500W and supplies high quality electric power. Its efficient and environmental protection 4 stroke OHV engine and high intensity body structure with new and optimised design make the machine run under a noise lower than 65 db, an overall weight of 45kg and a 10-hour continuous operation after a single refueling. The revolutionary application of " easy parallel connection " technology means the generator can be paralleled and combined to create higher output

Features

- 3300W (max.) 3000W (cont.)
- Perfect for construction sites or emergencies where perfect power is essential
- Useful for battery chargers, drills, grinders, saws and lighting
- Robust and portable, weighing in at 45kg
- Quiet operation - 65dB at full load
- Parallel link - capable for up to 6000W output
- Twin 230V outlet + 8V DC Outlet
- 10 litre tank for up to 10 hrs run-time
- Fuel saving smart throttle feature
- Recoil / Electric start for reliability
- 2 year warranty.